



Vol.
12

CISIN'S
NEW
CONDENSED EDITION

PRICE
50
CENTS



TV AND RADIO TUBE



INCLUDING
FOREIGN
SUBSTITUTIONS

SUBSTITUTION

Published by
HARRY G. CISIN
Amagansett, N. Y.

GUIDE

Cat. No. S 12

NEW TV & RADIO TUBE SUBSTITUTION GUIDE

CONDENSED EDITION - VOLUME 12

**By H. G. CISIN, E. E.
Consulting Engineer**

This new edition is an up-to-date, condensed substitution guide for the more widely used tubes. It is a compact, handy reference source in a form which permits it to be carried in coat pocket or tube caddy.

Section 1 includes tubes domestic and foreign, which can be substituted directly for U. S. A. tubes, without the necessity of any circuit or socket changes.

Section 2 lists foreign tubes and their U. S. A. equivalents.

Section 3 contains a list of tubes, many of them new, for which there are no DIRECT substitutes. However, by means of a unique consultation service described in this section, it is possible to obtain "indirect" equivalents -- tubes which will function well in place of the original ones.

Library of Congress Catalog Card Number: 64-24118

This book or any parts thereof, may not be reproduced in any form without written permission from the author.

Copyright under International Copyright Union (1910)

Copyright © 1955, 1957, 1959, 1961 and 1964 by Harry G. Cisin, Amagansett, N. Y. Printed in the United States of America.

**HARRY G. CISIN, Publisher
Amagansett, N. Y.**

SECTION 1

SUBSTITUTES FOR U.S.A. TUBES

Tube -- Substitute	Tube -- Substitute	Tube -- Substitute
00A - 01A, 200A, 300A, 40	1AD4 - DF62(f)	1D7 - 1C7*
01A - 00A, 00AA, 01B 40, UX201A, 501A	1AE4 - 1L4*(t), 1T4*(t), 1V4*(t)	1D7G - 1C7G*
0A2 - 0B2, 6073, 150C2(f), 6626, STV150/30(f)	1AF - 951	1D8 - 1B8
01B - 01A	1AF4 - 1L4*, 1U4*, 1T4*(t), 1AJ4(t), DF96(f), W25(f)	1D8GT - 1B8GT
0A2WA - 6073, 6626, 0A2	1AF5 - 1S5*(t)	1DN5 - 1U5
0A3 - VR75, 0B3, 5651	1AG5 - 1AJ5, 1AK5	1D21 - SN4
0A4 - 1267, Z300T(f)	1AH5 - DAF96(f), 1AF5	1E3 - DC89(f)
0B2 - 6074, STV10830(f), 0B2WA, 6627	1AJ4 - 1AF4, DF96(f)	1E4 - 1G4, 1H4(t)
0B2WA - 0B2, 6074, 6627	1AJ5 - 1AG5, 1AK5	1E4G - 1G4GT, 1H4G(t)
0B3 - VR90, 1266	1AK4 - 1AH4(t)	1E5 - KF35(f)
0C3 - VR105, 0C3W	1AK5 - 1AG5, 1AJ5	1E8 - 1C8
0D3 - VR150, 150C3(f)	1AN5 - DF97	1F5 - 1J5, KL35(f)
0E3 - 85AI(f)	1AM4 - 1AF4	1G3 - 1K3, 1B3, 1J3, 8016
0G3 - STV85/10(f)	1AX2 - 1AX2A, 1AX2B, 1X2(t)	1G4 - 1E4, 1H4(t)
0Y4 - 0Y4G, 0Z4A, 1005/CK1005	1AX2A - 1X2A, 1X2B	1G5 - 1J5, 1F5
0Y4G - 0Y4, 1005/CK1005, 0Z4A	1B3GT - 1G3, 1J3, 1K3, 8016, 2B3(t), DY30(f), 1N2, 1N2A, 1G3GT	1G6 - 1J6*(t)
0Z4 - 0Y4, 0Z4A, 1003, 0Z4G	1B4 - 1A4, 1E5, 32, 34	1H2 - 1X2, 1X2A, 1X2B
0Z4A - 1003, 0Y4, 0Z4, 0Z4G, 1005/CK1005	1B4P - 951	1H4 - 1E4(t)
0Z4G - 0Z4, 0Z4A, 0Y4, 1003	1B5 - 25S	1H5 - DAC32(f) HD14(f)
1A3 - DA90(f), 1D13(f)	1B7 - 1A7*, 1LC6	1HT4 - 6345
1A4 - 1B4, 1A4P, 1A4T, 32, 34	1B8 - 1D8	1J3 - 1B3, 1G3, 1K3, 8016
1A4P - 34, 1C4(f)	1C5 - 1A5*, 1Q5(t), DL35(f), N14(f)	1J5 - 1G5
1A4T - 1A4P	1C6 - 1A6	1J6 - 1G6*
1A5 - 1C5*, 1G4(t), 1Q5*	1C7 - 1D7*, KK32(f)	1K3 - 1G3
1A6 - 1C6*	1C8 - 1AE5*, 1E8	1L4 - 1AF4*, 1T4, 1U4, DF92(f)
1A7 - 1B7*, 1C7*, DK32(f), X14(f)	1D5 - 1E5	1L6 - 1U6*
1AB6 - 1AC6*, DK96(f)	1D5G - 1D5GP, 1D5GT, 1E5G, 1E5GP, 1E5GT	1LA4 - 1LB4
1AC5 - 1V5	1D5GP - 1D5G, 1D5GT, 1E5G, 1E5GT	1LA6 - 1LC6
1AC6 - 1AB6, DK92(f), X18(f)	1D5GT - 1D5, 1D5G, 1D5GP, 1E5G, 1E5GP, 1E5GT	1LB4 - 1LA4
		1LC5 - 1LG5, 1LN5
		1LC6 - 1LA6
		1LE3 - 1293*, 1LF3
		1LF3 - 1LE3

*Parallel heater circuits only. Underline: Good or better substitute. (f) Foreign.
(t) Temporary (emergency) substitute.

Tube	-- Substitute	Tube	-- Substitute	Tube	-- Substitute
1LG5	- 1LC5, 1LN5	2B4	- 885	3B24	- 3B24WA, 3B24A
1LN5	- 1LC5, 1LG5	2B7	- 2B7S	3BA6	- 3AU6
1M3	- <u>DL70(f)</u> , 1N3	2B7S	- 2B7	3BE6	- 3BY6(t)
1N3	- 1M3	2B25	- 1091	3BN4	- 3BN4A
1N5	- 1P5, 1D5(t), DF33(f), Z14(f)	2C21	- 1642, 33	3BT6	- 3AV6
1P5	- 1N5	2C23	- <u>10Y</u>	3BY6	- 3CS6
1Q5	- 1T5*, 1A5*, 1C5(t), DL36(f)	2C40	- 446, 446A, 446B	3BZ6	- 3BC5, 3BC6
1R4	- 1294	2C43	- 464A	3C2	- 3A3, 3B2
1R5	- <u>DK91(f)</u> , X17(f)	2C44	- GL464, 2C43	3C4	- 3V4, DL96(f), 1P1(f)
1S2	- 1H2, DY86(f), <u>1S2A</u>	2C50	- 2C52, 12SL7	3C5	- 3B5, 3Q5
1S2A	- 1H2	2C51	- 5670*, 6185, 6385, 6386	3C6	- XXB(f)
1S4	- DL91(f)	2C52	- 12SL7*, 12SN7(t), 12SX7(t), 2C50	3C45	- 6130, 5137, 45Z3
1S5	- 1AF5*, DAF91(f), IFD9(f)	2D21	- 2D21W, 5727 <u>2D21WA</u>	3CE5	- <u>3CB6</u> , <u>3CF6</u>
1S6	- 1T6	2D21W	- 2D21*, 5727, 2D21WA	3CF6	- <u>3BZ6</u> , <u>3CE5</u>
1T4	- 1L4, 1AF4*, 1U4, DF91(f), 1F3(f)	2E5	- 2G5	3CS6	- 3BY6
1T5	- 1A5, 1C5*, 1G4(t), 1Q5	2E25	- 2E25A	3D6	- 3LF4*, 1299*, DL29(f)
1T6	- 1S6	2E26	- 6893	3E5	- 3V4, 3C4, DL96(f), N25(f)
1U4	- 591Q, 1AF4*, 1L4, <u>1T4</u> , DF904(f)	2E26	- 6893	3LE4	- 3LF4
1U5	- 1DN5, DAF92(f)	2E30	- 5812	3LF4	- <u>3LE4</u> , 3D6*, 1299*
1U6	- 1L6	2E31	- <u>2E32</u>	3Q4	- 3S4, DL95(f), N18(f)
1V	- 6Z3	2E32	- <u>2E31</u>	3S4	- 3W4(f), N17(f), 3Q4
1V5	- 1AC5	2E35	- <u>2E36</u>	3Q5	- 3B5, 3C5, DL33(f)
1V6	- DCF60(f)	2E36	- 2E35	3S4	- 3Q4, DL92(f), N17(f), 1P10(f)
1W4	- A11B(f)	2E41	- <u>2E42</u>	3V4	- 3C4*, 3E5*, DL94(f) N19(f)
1W5	- 1V5(t)	2E42	- 2E41	4BC8	- 4BK7, 4BQ7, 4BQ7A, 4BS8, 4BZ8
1X2	- 1AX2(t), 1AX2A, 1X2A, 1X2B	2EA5	- 2CV5(f), 2EV5(f)	4BK7	- 4BC8, 4BQ7, 4BS8, 4BZ8
1X2A	- <u>1AX2</u> , <u>DY80(f)</u> , 1X2B	2G5	- 2E5	4BQ7	- 4BC8, 4BK7, 4BS8, 4BZ7, 4BZ8, 4BQ7A
1X2B	- <u>1AX2</u> , 1X2A, 1H2	2G21	- <u>2G22</u>	4BS8	- 4BC8, 4BK7, 4BQ7, 4BQ7A, 4BZ8
2A3	- 45, 5390, 2A3A, 2A3W	2G22	- <u>2G21</u>	4BX8	- 4BC8, 4BK7, 4BQ7, 4BS8, 4BZ8
2A3A	- 5930	2T4	- 2AF4, 2AF4A, 2AF4B	4BZ7	- 4BC8, 4BK7, 4BQ7, 4BS8, 4BZ8, 4BQ7A
2A3W	- 5930	2X2	- 879, 2B21(f), 143D(f), 2X2A, 2X2W	4BZ8	- 4BC8, 4BK7, 4BQ7, 4BS8
2A6	- 55*	2X2A	- 879, 2B21(f), 143D(f), 2X2	4CB6	- 4DT6(t), 4DE6
2A7	- 2A7S	2X2W	- 2X2	5AR4	- GZ34(f)
2AF4	- 2T4, 2AF4A, 2AF4B	3A3	- 3B2, 3C2	5AS4	- 5AS4A, 5AW4, 5U4GA, 5U4GB, 5V3, 5931, 5AU4, 5AX4GT, 5U4G
2AF4A	- 2AF4, 2AF4B, 2T4	3A4	- DL93(f)		
2AF4B	- 2AF4A, 2AF4, 2T4	3A5	- DCC90(f)		
2B3	- 1B3(t)	3AL5	- XAA91(f)		
		3AU6	- 3BA6, XF91(f)		
		3AV6	- 3BT6		
		3B2	- 3A3, 3C2		
		3B4	- HD30(f)		
		3B5	- 3C5, 3Q5		
		3B7	- <u>1291</u>		

*Parallel heater circuits only. Underline: Good or better substitute. (f) Foreign. (t) Temporary (emergency) substitute.

Tube	-- Substitute	Tube	-- Substitute	Tube	-- Substitute
5AU4	- 5AW4, 5U4GA, 5U4GB, 5V3, 5931, 5AS4, 5R4GY, 5T4, 5U4G, 5AS4A	5U8	- 5EA8	6AD5	- 6AE5, 6AF5, 6C5, 6J5, 6J5GT, 6J5WGT, 6P5
5AW4	- 5U4, 5AU4, 5U4GA, 5U4GB, 5V3, 5391, 5AS4, 5R4GY, 5T4, 5U4G, 5AS4A, 5W4	5V3	- 5AS4, 5AU4, 5AW4, 5U4GB	6AD6	- 6AF6
5AX4	- 5AS4, 5U4GA, 5U4GB, 5931, 5T4, 5U4G, 5W4, 5Y3, 5Y3GT, 5Y3G/GA, 5Z4	5V4	- 5V4GA, GZ32(f)	6AE5	- 6AD5, 6C5, 6J5, 6J5GT, 6J5WGT, 6P5
5BK7	- 5BQ7, 5B27	5W4	- 5W4GT, 5W4G	6AE8	- X79
5CG4	- 5Y4GA	5X3	- 5Z3, 80, 83, 83V, 1275	6AF4	- 6T4, 6AN4, 6AF4A
5CL8	- 5CL8A, 5CL8AGA	5X4	- 5X4GA, 5Y4G, 5Y4GA, 5Y4GT	6AF5	- 6AD5, 6AE5, 6C6, 6J5, 6P5
5R4G	- 5R4WGA, 5R4WGB, 5R4WGY, 5AW4, 5T4, 5AX4, 5U4G, 5AS4, 5Z4, 5931	5Y3	- 5Y3GT, 5Y3WGT, 5Y3WGTA, 5Y3WGTB, 5Y3GA, 5AW4, 5AX4, 5T4, 5AX4GT, 5V4, 5W4, 5Z4, 5931	6AF6	- 6AD6
5R4GY	- 5R4GYA, 5AW4, 5R4G	5Y4G	- 5Y4G, 5U4GA, 5U4GB, U50(f), 6087, 6106	6AG5	- 6AK5*, 6AJ5*(t), 6186, 6BA6, 6CE5, 6BC5, 6CF6, 6BD6, 6CB6, 6AH6, 6AS6(t), 6AS6W(t), 6BH6(t), 6BJ6(t), 5590*, 5591*, 9001*, 9003*, EF96(f)
5R4WGA	- 5R4WGB, 5R4WGY	5Z3	- 5X3, 80, 83, 83V, 1275	6AG7	- 6AK7, 6AG7Y
5R4WGB	- 5R4WGA, 5R4WGY	5Z4	- 5V4GA, 5V4G, GZ30(f)	6AH6	- 6BC5*, 6AJ5*(t), 6485, 6AK6*(t), 6AU6*(t), 6BD6*(t), 6AH6WA
5R4WGY	- 5R4WGA, 5R4WGB	6A4/LA	- 52, LA	6AJ4	- 6AM4
5T4	- 5AS4, 5AW4, 5AX4, 5R4G, 5U4G, 5U4GA, 5U4GB, 5W4, 5Y3, 5Z4, 5931	6A5	- 6B4	6AJ5	- 6CF6*(t)
5U4G	- 5AS4, 5AW4, 5AX4GT, 5U4WG, 5T4, 5U4GA, 5U4GB, 5V3, 5W4, 5Y3, 5931, U52(f), GZ34(f), H52(f)	6A6	- 6E6*, B63(f)	6AJ7	- 6AC7, 6AB7, 1852, 1853, 6SD7*, 6SE7*, 6SJ7*, 6SK7*, 6SS7*, 5693*
5U4GA	- 5AS4, 5AW4, 5AU4, 5AX4, 5T4, 5U4G, 5U4GB, 5V3, 5W4, 5Y3, 5Z4, 5931, H52(f), U52(f), GZ34(f)	6A7	- 6A7S	6AJ8	- ECH81(f), DP61(f)
5U4GB	- 5AS4, 5AU4, 5AW4, 5AX4, 5T4, 5U4G, 5U4GA, 5V3, 5Y3, 5Z4, 5931, U52(f)	6A8	- 6D8*, 6J8, 6K8, X63(f), 6A8G, 6A8GT	6AK5	- 6AG5*, 6AJ5(t), 6CF6, 6AK5WA, 6AK5W, 6BC5*(t), 5590*, 5591*, 9003, 5654, 6096, 408A, EF95(f)
		6AB4	- EC92(f)	6AK7	- 6AG7
		6AB5	- 6E5*(t), 6N5	6AK8	- 6T8, 6T8A, DH719(f), 6R6
		6AB6	- 6AC6*	6AL5	- 6AL5W, 5726, 6058, 6097, 6663, D77(f), DD6(f), EB91(f), EA91(f), 6D2(f), D152(f), DD7(f)
		6AB7/1853	- 6AC7/1852, 6AJ7, 6SD7*, 6SE7*, 6SJ7*, 6SK7*, 6SS7*, 5693*	6AM4	- 6AJ4
		6AB8	- ECL80(f), SN152(f)	6AM6	- 6064, EF91(f), SP6(f), 6FI2(f), 8D3(f), Z77(f)
		6AC5G	- 6AC5GT	6AM8	- 6AM8A
		6AC5GT	- 6AC5G		
		6AC6	- 6AB6*		
		6AC7	- 6AB7, 6AC7W, 6AJ7, 6SD7*, 6SJ7*, 6SK7*, 6SS7*, 1852, 1853, 6006*, (f), 6134, 5693*, 6F10		

*Parallel heater circuits only. Underline: Good or better substitute.

(f) Foreign. (t) Temporary (emergency) substitute.

Tube	Substitute	Tube	Substitute	Tube	Substitute
6AN4	- 6AF4, 6T4, 6AF4A	6BA6	- 6AU6, 6BD6, 6AG5, 6BC5, 6CG6, 6BA6W, 5749, 6136, EF93(f), HM04(f), 6660	6BL4	- 6AU4GTA, 6AX4(t)
6AN5A	- 6AN5WA			6BL6GT-	6BX7, 6SN7*, 6SU7*(t), 5592, 5591*(t), 6SL7(t), 6BL7GTA
6AN8	- 6AN8A	6BA8	- 6BA8A, 6AU8, 6AW8, 6BH8	6BK7A-	6BK7B, 6BQ7, 6BQ7A, 6BS8, 6BZ7, 6BZ8, X155, 6BC8
6AQ4	- <u>EC91(f)</u> , 6L34(f)	6BC5	- 6CE5, 6CF6, 6AG5(t), 6AJ5*(t), 6AK5*(t), 9001*(t), 9003*(t), 5591*, 5654*, 6AS6*(t)	6BM5	- 6AQ5
6AQ5	- 6BM5, 6AQ5A, <u>6AQ5W, 6BF5*(t)</u> , 6005, 6669, <u>EL90(f)</u>	6BC8	- 6BQ7A, 6BS8, <u>6BQ7GB, 6BK7,</u> 6BK7A, 6BK7B, 6BZ7, X155	6BM8	- <u>ECL82(f)</u>
6AQ6	- 6AT6*, 6AV6*, 6BF6*, 6BK6*, 6BT6*, 6BU6*, 6066*, A4375A, D28			6BN5	- <u>EL85(I)</u>
6AQ8	- <u>ECC85(f)</u> , B719(f)			6BN8	- 6BX8
6AR6	- 6AR6WA, 6098, <u>6098W, 6384</u>	6BD4	- <u>6BD4A, 6BK4,</u> 6BD4A - 6BK4	6BQ5	- <u>EL84(f)</u> , N709(f)
6AS6	- <u>6AS6W, 5725,</u> 7752	6BD5	- 6AU5*(t), 6AV5*(t)	6BQ6G-	<u>6BQ6GT, 6BQ6GTA,</u> <u>6BQ6GTB, 6CU6,</u> <u>6DQ6, 6DQ6A</u>
6AS7G	- 6080, 6080WA, WB	6BD6	- 6AH6*(t), 5749	6BQ7	- 6BC8, 6BK7, 6BS8, 6BK7A, 6BQ7A, 6BZ7, 6BZ8, X155
6AT6	- <u>6AV6, 6066,</u> <u>DH77(f)</u> , <u>EBC90(f)</u> , 6BF6, 6BK6, 6BT6, 6BU6	6BE6	- 5915, EK90(f), 6BY6, 5750	6BQ7A	- 6BS8, 6BZ7, 6BC8, 6BK7, 6BK7A, 6BZ8, X155
6AT8	- 6AT8A	6BE7	- EQ80(f)	6BR5	- EM80(f)
6AU4	- 6AX4, 6BL4, 6W4, 6AU4GTA	6BE8	- 6BE8A	6BR8	- 6CL8A, <u>6BR8A</u>
6AU5	- 6AV5*, 6BD5*	6BF5	- 6AQ5*(t), 6AQ5A*(t)	6BS7	- 8D7(f)
6AU6	- 6BA6, 6BD6, 6AU6WGT, 6AU6A, 6AU6WB, 6136, 5749, 6163, 5590*, 7543(f), 5591*, 9001*, 6AG5(t), 9003*	6BF6	- 6BU6, A-4442	6BS8	- 6BC8, 6BK7, 6BK7A, 6BQ7, 6BQ7A, 6BZ8, X155
6AU7	- 6AU7A, 7AU7	6BF7	- 6BG7	6BT6	- 6066, 6BK6, 6AQ6*, 6BD7*, 6AV7
6AU8	- 6AW8, 6BA8, 6BH8	6BG6G	- 6CD6*(t), 6DN6, 6BG6GA	6BU6	- 6BF6
6AV4	- 6BX4, 6X4	6BG7	- 6BF7	6BW4	- <u>EZ81*(f)</u> , 6CA4
6AV5	- 6AU5*, 6BD5*, 6AV5GA	6BH6	- 6BJ6, 6AS6*, 6BC5*(t), 6CB6*, 6265*, 6661, E90F(f)	6BW7	- <u>6BX6</u>
6AV6	- 6AT6, 6AQ6*, 6066, 6BT6, <u>EBC91(f)</u>	6BH8	- 6AU8, 6AW8, 6BA8	6BX4	- 6X4, 6AV4*, 6Z31
6AW8	- 6AU8, 6AW8A	6BJ5	- N78(f)	6BX6	- 6BN7, 6BY7, EF80(f), Z152(f), Z179(f)
6AX4	- 6AU4, <u>6BL4, 6U4,</u> 6DA4	6BJ6	- 6BH6, 6BA6*, 6AS6*, 6BC5*(t), 6CB6*, 6BA6W, 5749, 6136, 6662	6BX7	- 6BL7
6AX5	- 6W5*, 6X5*, 6ZY5*, 1274	6BJ8	- 6BN8	6BX8	- 6BC8, 6BE6, 6BK7, 6BQ7, 6BS8, 6BZ7, 6BZ8, X155
6AX8	- 6AU8, 6U8*, 6U8A*	6BK4	- 6BD4A	6BY6	- 6CS6, 5915
6B4	- 6A5	6BK6	- 6066, 6AT6, 6AV6, 6BF6, 6BT6, 6BU6	6BY7	- 6BX6, EF85(f), W179(f)
6B6	- <u>6Q7, 6Q7G, 6Q7GT,</u> <u>DH63(f)</u>	6BK7	- 6BK7B, 6BQ7, 6BQ7A, 6BS8, 6BZ7, 6BZ8, X155, 6BC8	6BZ6	- 6CB6, <u>6DE6</u> <u>6CF6,</u> EF190(f)
6B8	- 6B8G, EBF32(f)				

*Parallel heater circuits only. Underline: Good or better substitute. (f) Foreign. (t) Temporary (emergency) substitute.

Tube	Substitute	Tube	Substitute	Tube	Substitute
6BZ7	- 6BQ7A, 6BQ7, 6BK7A, 6BK7, 6BC8, 6BZ8, 6BQ8, 6BS8, X155	6CG8	- 6CG8A	6F5	- 6F5GT, H63(f)
6BZ8	- 6BC8, 6BK7A, 6BK7, 6BS8, 6BZ7, 6BQ7A, 6BQ7, 6BQ8, X155	6CH6	- 6132, EL821(f), EF82(f), M8135(f), EL822(f)	6F6	- 6K6*, 6L6*, 6U6*, 6V6*(t), 1611, 5881*, 1621, 1622*, KT63(f), 6F6G, 6F6GT
6C4	- 5610, 6135, 9002(f), EC90(f), 6C4W, L77(f), 6100, 6C4WA	6CJ6	- EL81(f)	6F7	- 6F7S
6C5	- 6AD5, 6AE5, 6AF5, 6L5*	6CK6	- EL83(f)	6F7S	- 6F7
6C6	- 6D6, 77, 78, 1221, 1603, 7700	6CL6	- 6677	6F8	- 6C8*
6C8	- 6F8*	6CL8	- 6CL8A	6G5	- 6E5, 6T5, 6U5, 6AB5*
6CA4	- EZ81*(f), 6BW4*	6CN6	- EL38(f)	6G6	- 6F6, 6K6, 6V6
6CA7	- 6L6*, EL34(f), 6L6GB*, 6L6GC*, KT66*(f), 5881*, 7027*, 6L6G, 6L6GA, 7D11(f), 12E13(f)	6CQ6	- EL38(f), 9D6(f)	6G7	- 89RS(f)
6CB5	- 6CB5A	6CR4	- A2521	6GH8	- 6EA8
6CB6	- 6DE6, 6CB6A, 6BZ6, 6DC6, 6AS6*(t), 6BH6*(t), 6BJ6*(t), 6CF6, 6AG5, 6BC5, 6AJ5(t)*, 6AK5*, 5590*, 5591*, 5654*	6CS6	- 6BY6, 6BE6, EH90(f)	6H5	- 6U5, 6G5, EM35(f), Y61(f)
6CD6G	- 6DN6, 6BG6*, 6CD6-GA	6CT7	- EAF42(f)	6H6GT	- EB34(f), D63(f), 6H6WGT, 6H6GT
6CD7	- EM34(f)	6CU6	- 6DQ6G, 6BQ6GT, 6DQ6A, 6BQ6GTA, 6BQ6G TB, 6DQ6, 6DQ6A	6J4	- 6J4WA
6CF6	- 6CB6, 6AG5, 6AK5, 6BC5, 5590, 5591, 5654, 9001(t), 9003(t), 6AJ5*(t), 6186	6CU7	- ECH42(f)	6J5GT	- 6AD5, 6AE5, 6AF5, 6C5, 6L5*, 6P5, 6J5WGT, L63(f)
6CG6	- 6AG5, 6AU6, 6BA6, 6BC5, 6BD6, 6AH6*, 6AK5*, 5591*, 5654*, 5590*(t), 9001*(t), 9003*(t), 6AJ5*(t)	6CV7	- EBC41(f)	6J6	- 5964, 6101, 6J6A, 6J6W
		6CW5	- EL86(f)	6J7	- 6J7GT, 6K7, 6S7*, 6U7, 6W7*, 6J7G, 7000, 1223, 1620
		6CW7	- ECC84(f)	6J8	- 6A8, 6D8*, 6K8
		6D6	- 6C6, 77, 78	6K4	- 6AD4
		6D7	- 6E7	6K6	- 6F6*, 6L6*(t), 6U6*, 6V6*, 6G6*(t), 1621*, 5871
		6D8	- 6A8*, 6J8*, 6K8*, X73M(f)	6K7	- 6J7, 6S7*, 6U7, 6W7*, 5732, 6K7G, 6K7GT, 1NR81(f)
		6DA6	- EF89(f)	6K8	- 6A8, 6J8
		6DC6	- 6BZ6, 6CB6, 6DE6	6L4	- 6F4(t)
		6DC8	- EBF89(f)	6L5	- 6AD5*, 6AE5*, 6C5*
		6DE6	- 6BZ6, 6CB6, 6DC6	6L6	- 6F6*, 6K6*, 6U6*, 6V6*, 1614, 6L6W, KT66*(f), 5881, 1622, 1621*, 5932, 6550, 7027*, 6L6G, 6L6GB, 6L6GC, 6L6W
		6DG6	- 6W6, 6K6*, 6V6*	6L6GA	- 6L6GAY, 6L6GB, 6L6WGA
		6DJ8	- ECC88(f)		
		6DN6	- 6CD6, 6BG6, 6BG6GA		
		6DQ6	- 6BQ6GT, 6BQ6GTA, 6CU6, 6DQ6A		
		6DR8	- EPF83(f)		
		6DS8	- ECH83(f)		
		6E5	- 6T5, 6U5, 6G5, OSW3110(f)		
		6E6	- 6A6, 6B3(f)		
		6ES6	- EF97(f)		
		6E7	- 6D7		
		6E8	- ECH35(f)		
		6E3A	- 6GH8 (except R. F. osc. and mixer)		
		6F4	- 6L4(t)		

*Parallel heater circuits only. Underline: Good or better substitute. (f) Foreign. (t) Temporary (emergency) substitute.

Tube	Substitute	Tube	Substitute	Tube	Substitute
6L6GB	- 6L6WGB	6SN7GT-	6BL7*, 6BX7*,	6W2	- 6X2
6L6GT	- 6L6WGT		6SL7*, 6SL7GT*,	6W4	- 6AX4, 6U4, 6AD4
6L7	- 1612, 6L7G		6SN7GT,	6W5	- 6AX5*, 6X5*,
6N6	- 6AB6*		6SN7WGT,		6ZY5*
6N7	- 6Y7, 6Z7, 1635*,		6SN7GTA, 5692,	6W6	- 6G6*, 6L6(t)*,
	6N7GT		6SN7GTB, 5691(t),		5881*, 6F6*(t),
6N8	- EBF80(f)		6180, B65(f),		6K6*, 6U6*, 6V6*,
6P5	- 6AD5, 6AE5,		ECC33*(f)		6Y6G, 6Y6GA,
	6AF5, 6C5, 6J5,	6SN7GTA - 6SN7WGTA			6Y6GT
	6L5*	6SQ7	- 6SR7, 6ST7*,	6W7	- 6J7*, 6K7*, 6U7*,
6P8G	- ECH35(f)		6SZ7*, 6SQ7G		6S7
6Q4	- EC80(f)	6SR7	- 6SQ7, 6SZ7*,	6X2	- 6W2, EY51(f),
6Q5G	- 884		6ST7*, 6SR7GT		R12(f), U43(f)
6Q7	- 6B6, 6R7, 6T7*,	6SS7	- 6SJ7*, 6SK7*,	6X4	- 6X4W, 6BX4,
	6V7, DH63(f)		6SS7GT		6AV4*, 6063,
6R4	- EC81(f)	6ST7	- 6SQ7*, 6SR7*		6202, EZ90(f)
6R7	- 6Q7, 6T7*6V7	6SU7	- 6SL7, 6SN7(t),		U78(f)
6R8	- 6T8, 6AK8, 6T8A		6113	6X5	- 6X5GT, 6AX5*,
6S4	- 6S4A	6SV7	- 6SF7		6W5*, 6ZY5*,
6S7	- 5732*, 6W7, 6J7*,	6SZ7	- 6SQ7*, 6SR7*,		1274*, 6X5WGT,
	6K7*, 6U7*,		6ST7		EZ35(f), U147(f),
	K1W61(f)	6T4	- 6AN4, 6AF4		U70(f)
6SA7GT-	5961, 6SB7Y,	6T5	- 6AB5*, 6E5, 6U5,	6X8	- 6X8A
	6SA7WGT		6G5, 6N5	6Y5	- 6Z5 (6-volt use
6SB7Y	- 6SA7, 5961	6T7	- 6B6*6Q7*, 6R7*,	only)	
6SD7	- 6AB7*, 6AC7*,		6V7*	6Y6	- 6K6*, 6L6*, 6U6*,
	6SS7*, 6SE7,	6T8	- 6R8, 6AK8,		6V6*, 6G6*(t),
	6SJ7, 6SK7, 5693,		EABC80(f), 6T8A		6Y6G, 6Y6GA,
	1852*, 1853*	6U3	- EY80(f)		6Y6GT
6SF7	- 6SV7	6U4GT	- 6AX4GT, 6DA4,	6Y7	- 6N7*, 6Z7*, 1635
6SG7	- 6AB7*, 6AC7*,		6W4	6Z3	- 1V
	6006, 6SG7GT,	6U5	- 6G5, 6AB5*, 6E5*,	6Z4	- 84, 98
	6SH7*		6N5*, Y61(f)	6Z5	- 6Y5(6-v use only)
6SH7	- 6AB7*, 6AC7*,	6U6	- 6F6*, 6G6*(t),	6Z7	- 6N7*, 6Y7*
	6SG7, 6006,		6K6*, 6L6*(t),	6ZY5	- 6AX5*, 6W5*, 6X5*
	6SG7GT, 6SJ7,		6V6*, 6W6*(t),		1274
	6SK7, 6SH7GT		5881*	7A4	- 7B4, XXL
6SJ7	- 5693, 6SK7,	6U7G	- 6K7GT/G, 6U7GT	7A5	- 7B5*, 7C5*
	6SS7*, 6006,		6J7G, 6J7GT,	7A7	- 7H7, 7L7, 7B7*,
	6SJ7GT, 6SJ7Y		5732		7C7*
6SJ7GT-	6SJ7WGT	6U8	- 6AX8, 6U8A,	7A8	- 7B8*, 7J8*, 7S7*
6SK7	- 6AB7*, 6AC7*,		ECF82(f),	7AB7	- 1204
	6SG7, 6SH7, 6SJ7,	6V3	- 6V3A	7AD7	- 7AG7*(t), 7AH7*(t),
	6SS7*, 6137, 6006,	6V4	- EZ80(f)		7AJ7*(t), 7AK7*(t),
	6SK7GT, 6SK7W	6V6	- 6F6*, 6G6*(t),		7B7*(t), 7C7*(t),
6SL7GT-	6SL7WGT, 6113,		6K6, 6L6*, 6U6*,		7G7*(t), 7H7*(t),
	6SN7*, 6SU7,		6W6*, 6Y6*, 1621*,		7L7*(t), 7I7*(t),
	5691*, 6592(t)		1622*, 5871, 5992,		7V7*(t)
	6SL7W,		6V6GTA, 6V6GT	7AF7	- 7F7
	6SU7GTY	6V7	- 6R7, 6T7*		7N7*

*Parallel heater circuits only. Underline: Good or better substitute. (f) Foreign. (t) Temporary (emergency) substitute.

Tube	Substitute	Tube	Substitute	Tube	Substitute
7AG7	- 7AH7, 7B7(t), 7C7(t), 7AJ7*(t), 7AK7*(t), 7G7*, 7H7*, 7L7*, 7T7*, 7V7*	7T7	- 7A7, 7B7*, 7G7*, 7H7, 7L7, 7V7, 1232*, 1273	12AU6	- 12BA6, 12BD6, B329(f), ECC82(f), HF94(f)
7AH7	- 7AG7, 7B7(t), 7C7(t), 7AJ7*, 7AK7*(t), 7G7*(t), 7H7*(t), 7L7*(t), 7T7*(t), 7V7*(t)	7V7	- 7B7*, 7C7*, 7G7, 1231	12AU7	- 12AU7WA, 5814, 5814A* 6067, 6189, 6680, 5963, 12AZ7*(t), 12AU7A, 12AT7, 12AX7, 12AY7, 12AV7*
7AJ7	- 7AH7*, 7AK7*(t), 7B7*(t), 7C7(t), 7G7*(t), 7V7*(t). 7H7, 7L7, 7T7	7X7	- XXFM(f)	12AV6	- 12AT6, 12BK6, 12BT6, 12BU6, 12BF6(t), HBC91(f)
7AK7	- 7AH7(t)*, 7AJ7*(t), 7B78(t), 7C7*(t), 7G7*(t), 7H7*(t), 7L7*(t), 7T7*(t), 7V7*(t)	7Y4	- 7Z4*	12AV7	- 5965, 12AZ7, 12AT7* 6829, 6414, 12AU7*, 12AX7*, 12AY7*, 12BH7*, B339*(f)
7AU7	- XCC82(f)	7Z4	- 7Y4	12AX4GT	- 12AX4GTA
7B4	- 7A4, XXL	8A8	- LZ319(f), PCF80(f), 30C1(f)	12AX7	- 12AT7, 12AU7, 12AY7, 12AV7*, 12BH7*, 12AZ7*, 12AD7, 5751*, 6057, 6681, ECC83(f)
7B5	- 7A5*, 7C5*	8AU8	- 8AW8, 8BA8, 8BH8, 8AU8A	12AY7	- 12AT7, 12AU7, 12AV7*, 12AX7, 12BH7*, 6072*
7B6	- 7E6	8AW8	- 8AU8, 8BH8	12AX7GT	- 12AX7GT
7B7	- 7AH7, 7C7, 7H7*, WG149(f)	8BA8	- 8AU8, 8AW8	12AZ7	- 12AT7*, 12BH7*, 12AU7*(t), 12AX7*(t), 12AY7*(t), 12AV7
7B8	- 7A8*, 7J7, 7S7	8BH8	- 8AU8, 8AW8	12B4	- 12A4, 12B4A
7C4	- 1203A	9A8	- PCF80(f)	12B6	- 12B6W
7C5	- 7A5*, 7B5*	9AK8	- PABC80(f)	12B7	- 14A7
7C6	- 7B6*, DH149(f)	9AQ8	- PCC85(f)	12BA6	- 12AU6, 12BD6, HF93(f)
7C7	- 7B7, 7H7	9U8	- PCF82(f), 9U8A	12BD6	- 12AU6, 12BA6
7E5	- 1201	10	- 10Y, RK10, 50, 210, 310	12BE6	- HK90(f)
7E6	- 7B6, 7C6*	10Y	- 10, RK10, 50, 210, 310, 410, 2566A, 2C23	12BF6	- 12BU6, 12AT6(t), 12AV6(t), 12BK6, 12BT6
7E7	- 7R7	12A	- 71A	12BH7	- 12AT7*, 12AU7*, 12BH7A, 12AV7*, 12AX7*, 12AY7*, 12AZ7*
7F7	- 7AF7, 7N7*	12A4	- 12B4	12BK6	- 12BU6, 12BT6, 12AT6, 12AV6, 12BF6(t)
7F8	- 7F8W	12A8	- 12K8		
7G7	- 7A7*, 7B7*, 7C7*, 7H7*, 7L7*, 7V7, 1232*, EF22(f)	12AC5	- UF41(f)		
7G8	- 1206	12AC6	- 12AF6		
7H7	- 7A7, 7B7*, 7C7*, 7L7, 7T7, 7V7*, 1273	12AD6	- 12AG6		
7J7	- 7B8, 7S7	12AD7	- 12AX7*		
7L7	- 7A7, 7G7*, 7H7, 7T7, 7V7*	12AE6	- 12AT6, 12AV6		
7N7	- 7AF7*, 7F7*	12AF6	- 12AC6		
7R7	- 7E7	12AF7	- 6679		
7S7	- 7B8, 7J7, X148(f), X81M(f)	12AG6	- 12AD6		
		12AK7	- 12AZ7*, 12AX7, 12AY7, 12AD7		
		12AT6	- 12AV6, 12BK6, 12BF6(t), 12BT6(t), 12BU6(t), HBC90(f)		
		12AT7	- 12AT7WA, 6060, 6201, 6679, 12AU7, 12AV7, 12AX7, 12AY7, 12AZ7*, ECC81(f) B309(f), B152(f), 12BH7*		

*Parallel heater circuits only. Underline: Good of better substitute. (f) Foreign. (t) Temporary (emergency) substitute.

Tube	Substitute	Tube	Substitute	Tube	Substitute
12BQ6	12BQ6GA, 12BQ6GTA, 12BQ6GTB, 12CU6, 12DQ6, 12CH6	12SN7	12SX7, 12SL7*(t), 12SN7GT, 12SN7GTA, B36(f)	25A6	25B6, 25C6, 25L6, 5824
12BT6	12AT6, 12AV6, 12BK6, 12BU6, 12BF6(t)	12SQ7	12SR7, 12SW7(t)	25A7	32L7
12BU6	12AT6, 12AT6(t), 12AV6(t), 12BK6(t), 12BT6(t)	12SR7	12SQ7, 12SW7, 12SR7GT	25AV5GT	25AV5GA
12BV7	12BY7, 12BY7A	12SW7	12SQ7(t), 12SR7	25AX4	25U4, 25W4
12BY7	12BY7A, 12BV7	12SX7	12SN7, 12SL7*(t)	25B5	43
12BZ7	12AX7*	12SY7	12SA7	25B6	25A6, 25G6, 25L6, 25N6, 5824
12DQ6	12BQ6, 12CQ6	12W6	12L6, 1632	25BQ6	25B6, 25G6, 25BQ6GA, 25BQ6GTB, 25CU6, 25DQ6
12C5	12CA5, 12CU5, 12R5	14A7/12B7	1280, 1284, 12B7, 14C7, 14H7	25BQ6GA	25BQ6GTB, 25CU6, 25DQ6
12CA5	12C5	14AF7/XXD	14F7, 14N7*	25BQ6GT	25BQ6GA, 25BQ6GTB, 25CU6, 25DQ6
12CU5	12C5	14B6	14E6	25C5	25CA5
12CU6	12BQ6, 12DQ6	14B8	14J7, 14S7	25C6	25A6, 25B6, 25L6, 5824
12D4	12AX4, 12AX4GTA	14C5	14A5*	25CA5	25C5
12DQ6	12BQ6, 12BQ6GA, 12BQ6GTA, 12BQ6GTB, 12CU6, 12CH6	14C7	14B7, 1284, 14A7, 14A7, 14H7, 1280	25CD6	25DN6
12DT7	7025	14E6	14B6	25CU6	25BQ6, 25DQ6, 25BQ6G, 25BQ6GA, 25BQ6GT, 25BQ6GTB
12E5	1626*, 12J5, 12J5GT	14E7	14R7	25DN6	25CD6
12G4	12H4	14F7	14R7, 14AF7/XXD	25DQ6	25BQ6, 25BQ6G, 25BQ6GA, 25BQ6GT, 25BQ6GTB, 25CU6
12H4	12G4	14H7	1280, 1284, 14A7	25L6	6046, 25A6, 25B6, 1632, 25W6, 5824, KT32(f), 13DI(f)
12J5	1626*, 12E5, 12J5GT, 12J5WGT	14J7	14B8, 14S7	25S	1B5
12J7	12K7	14K7	UCH42(f)	25U4	25AX4, 25W4
12K7	12J7, W76(f)	14L7	UBC41(f)	25W4	25U4, 25AX4
12K8	12A8, X71M(f), X76M(f)	14N7	14AF7/XX2*	25W6	25L6, 6046, 25A6, 25B6, 25C6
12L6	12W6, 1632	14R7	14E7	25Y5	25Z5
12L8	1644	14S7	14B8, 1J7	25Z5	25Y5
12SA7	12SY7	14W7	12B7, 14A7, 14C7, 14H7, 1280, 1284	25Z6	25Z6GT, 25Z6WGT, 35Z6(t)
12SC7	1634	15A6	PL83(f)	26	126, 326, UX26, 226
12SG7	12SH7, 12SJ7, 12SK7	16A5	PL82(f), N329(f)	26A6	26CG6
12SH7	12SG7, 12SJ7, 12SK7	7DQ6	17DQ6GA, 17DQ6A	26BK6	26C6(t)
12SJ7GT	12SJ7	17Z3	PY81(f)	26C6	26BK6(t)
12SK7	12SG7, 12SH7, 12SJ7, 12SK7GT	19AQ5	HL90(f)	26CG6	26A6
12SL7	2C52*, 12SL7GT VT289	19AU4	19AU4GTA		
		19BG6	19BG6G, 19BG6GA		
		19C8	19T8		
		19T8	18C8		
		19X3	19Y3, 19U3(f), PY80(f), U152(f)		
		19Y3	19X3, U154(f), PY82(f), U319(f)		
		20	X99*		
		21A6	PL81(f), N152(f), N359(f)		
		24A	35/51(t) 3924		

*Parallel heater circuits only. Underline: Good or better substitute. (f) Foreign. (t) Temporary (emergency) substitute.

Tube	-- Substitute	Tube	-- Substitute	Tube	-- Substitute
27	- 56, 3373	71A	- 482, 483	1206	- 7G8
28F	- 28D7W, <u>1283</u>	75	- 6C6(t), 85(t)	1221	- <u>6C6</u> , <u>77</u>
28D7W	- <u>28D7</u> , <u>1238</u>	76	- 37	1223	- 6J7
30	- 31*	77	- <u>6C6</u> , 1221	1229	- <u>1A4</u> , <u>1B4</u> , <u>32</u> , <u>951</u>
31	- 30*, 3872	78	- <u>6D6</u>	1230	- <u>30</u>
32	- 1A4, <u>1B4</u> , 951, 3873	80	- <u>83V</u> , 83, 5Z3, 3841	1231	- <u>7G7</u> , 7V7
32L7	- <u>25A7</u>	81	- <u>10(T)</u> , 50(t)	1232	- 7G7*
33	- 1F4*, 950*	82	- 2A3(t), 45(t), 1006	1238	- 28D7
34	- 1A4, <u>1B4</u> , 32, 951	83	- <u>5Z3</u>	1266	- 0B3
35/51	- 24A	83V	- 5Z3, 80, 83	1267	- 0A4
35A5	- 50A5(series fil.)	84	- 6Z4	1273	- 7A7, 7AJ7, 7H7, 7L7, 7T7
35B5	- 50B5(series fil.)	85	- 75	1274	- 6AX5*, 6W5*, 6ZY5*, 6X5
35Z5	- 50Z6(series fil.)	85AS	- 85	1275	- 5Z3, 5X3, 80, 83, 83V
35L6	- 50C6, 50L6	89	- <u>89Y</u>	1280	- 12B7, 1284
35Z5	- 45Z5(series fil.)	98	- 84	1284	- 12B7, 1280
36	- 39/44, U76(f)		117L7GT- 117L7/M7GT	1291	- 3B7
37	- 76		117L7/M7GT - 117L7GT	1293	- <u>1LE3</u> *
38	- 38A, 4612		117N7GT- 117P7GT	1294	- 1R4
39/44	- 36, 39A, U76(f)		117P7GT- 117N7GT	1299	- 3D6
40	- 00A, 01A, 12A		182B/482B- 71A, 183/483	1612	- <u>X64</u> (f), 6L7(t)
40A1	- 40B2		183, 483 - 182B/482B, 71A	1614	- 6L6, 5881, EL35(f)
40B2	- 40A1		408-A - 6AK5(t)	1620	- 6J7, ECH42(f)
41	- 42		410 - 10Y	1621	- 6F6, 5581*, 6K6*, 6L6*, 6V6*
42	- 6B5, 41		446 - 446A, 446B, 2C40	1622	- 6L6, 6F6*, 6V6*, 5881
44	- 49/44		446A - 446B, 446, 2C40	1626	- <u>12E5</u> *, 12J5*
45	- 2A3, 3921		446B - 446A, 446, 2C40	1632	- 12L6, 12W6
45Z3	- 6130		464 - 2C44	1634	- 12SC7(t)
45Z5	- <u>35Z5</u> (series fil.)		464A - 2C43	1635	- 6Y7, 6N7*
50	- 10, 3871		807 - 5933, QV05-25(f) 807W	1639	- EBC33(f), DL63(f), VR55(f)
50AX6	- 50Z6		807W - 5933, 807, QV05-25(f)	1642	- 2C21
50B5	- A4388		807WA - 5933WA	1644	- 12L8
50C5	- HL92(i)		884 - 6Q5	2050	- 2051, <u>2050W</u>
50C6	- 50L6		885 - 2B4	2566A	- <u>10Y</u>
50L6	- 50C6		950 - 1F4, 33*	3373	- 27
50Y7	- 50Z7		951 - 1B4P/951	3841	- 80
50Z6	- 50AX6		954 - 956, VR-95(f)	3871	- 50
50Z7	- 50Y7		955 - 5731(t)	3872	- 30
53	- 5608-A		955A - 5731	3873	- 32
55	- 2A6		956 - 954, VR-95(f)	3921	- 45
55S	- 2A6, 55		957 - 958A*	3924	- 24A
56	- 27, 185		958A - 957*	4612	- 38
56AS	- 37*, 76*		1005/CK1005 - OY4, OZ4A	5137	- 6130
56S	- 27, 56		1091 - 2B25	5551	- 5551A, 5551/652
57	- 58		1201 - 7E5, 1201A		
57AS	- 6C6*, <u>77</u> *		1203 - <u>7C4</u> , <u>1203A</u>		
57S	- 57, 58		1204 - <u>7AB7</u>		
48	- 57(t)				
58AS	- 6D6*, <u>78</u> *				
58S	- <u>57</u> , <u>58</u>				

*Parallel heater circuits only. Underline: Good or better substitute. (f) Foreign. (t) Temporary (emergency) substitute.

Tube	--	Substitute	Tube	--	Substitute	Tube	--	Substitute
5590	-	6BC5*, 5591, 9001, 9003, 6AG5*(t), 401A, 6CF6*	5824	-	25B6, 25L6, 5829 - <u>5829WA</u> 5838 - 5839* 5839 - 5838*	6006	-	6SG7
5591	-	5590, 9001, 9003, 6AG5*, 6BC5*(t), 6AK5, 5654, 6CF6*	5840	-	5899, 5900, 5901, 5840A, EF72(f)	6028	-	408A, 6028/408A
5608A	-	53	5842	-	5842/417A	6046	-	25L6, 5824
5610	-	6C4, 6C4WA	5847	-	5847/404A, 404A	6057	-	12AX7, 5751
5633	-	SN-944(f), 5634	5861	-	1D03-10(f), EC55(f)	6058	-	6AL5, 5726
5634	-	SD128E(f), 6533	5871	-	6V6, 5992	6060	-	12AT7, 6201
5636	-	5636A	5881	-	1622, 5932, 1621*, 6K6(t), 6F6(t), 6U6(t), 6V6(t), 6L6WGB	6061	-	6V6
5641	-	5641A, EY70(f)	5670	-	5670WA, 2C51 6CC42(f)	6063	-	6X4
5647	-	6489, EA71(f), SN946(f)	5670WA-	-	5670, 2C51, 6CC42(f)	6064	-	6AM6
5651	-	5651WA, 0A3	5672	-	5678	6066	-	6AT6
5654	-	6AJ5, 6AK5, 6096, 5591, 6AK5W, EF95(f)	5676	-	5677*	6067	-	5814*, 12AU7
5685	-	C6J, A	5677	-	5676*	6072	-	12AY7
5692	-	6SN7, 6180	5678	-	5672	6073	-	0A2
5693	-	6SJ7	5687WA-	-	5687	6074	-	0B2
5702	-	5784	5691	-	6SL7*, 6SN7(t)	6080	-	6AS7G, 6080WA, 6080WB
5703	-	5703WA, 5703WB, 6149	5899	-	5899A, 5840, 5900, 5901, EF71(f)	6087	-	5Y3GT
5718	-	EC70(f), 6778	5900	-	5840, 5899, 5901	6095	-	6AQ5W, 6AQ5, 6005, EL90(t), M8245(f), N727(f)
5725	-	6AS6W, 6AS6, 6187	5901	-	5840, 5899, 5900	6096	-	6AK5, 5654, DP61(f), E95F(f)
5726	-	6AL5W, 6AL5, 6058, 6097	5910	-	5840, 5899, 5900	6097	-	6AL5, 5726, 6663, D2M9(f), 6038, DD6(f), EAA91(f), QD77(f)
5727	-	2D21W, 2D21	5915	-	1U4	6098	-	6AR6WA, 6098W, 6AR6
5731	-	955A(t)	5920	-	6BY6, 6BE6 E90CCF(f), ECC960(f)	6100	-	6C4, 6C4WA, EC90(f), QL77(f)
5732	-	6K7, KTW63(f), W61(f), W63(f)	5930	-	2A3, 2A3W	6101	-	6J6, 6J6WA, ECC91(f), M8081(f)
5749	-	6BA6W, 6BA6, EF93(f), W727(f), PMO4(f)	5931	-	5U4GB	6105	-	5AZ4, 5W4, 5Y3, U50(f)
5750	-	6BE6, 6BE6W	5932	-	6L6, 5881	6106	-	5Y3GT
5751	-	5751WA, 12AX7, 6057, 5751A	5933	-	807, 5933WA, 807WA	6107	-	BS212(f)
5751A	-	12AX7, 5751, 6057	5933WA-	-	807WA	6108	-	BS213(f)
5651WA	-	12AX7, 6057, 5751	5961	-	6SA7	6109	-	BS404(f)
5784	-	5784WA, 6150	5963	-	12AU7	6113	-	6SL7, 6SU7, ECC35(f)
5812	-	2E30	5964	-	6J6	6130	-	3C45, 5137, 45Z3, TG30(f)
5814	-	12AU7, 5814WA, 12AU7A, 6067, ECC82(f)	5965	-	12AV7, 6829, 6414	6132	-	6CH6
5814A	-	12AU7, 5814 5814WA, 12AU7A	5992	-	6V6*, 5871*	6134	-	6AC7
			5998	-	6AS7*, 421A, 6000 - 6000W	6135	-	6C5
			6005	-	6AQ5W, 6AQ5, 6095	6136	-	6AU6, 6AU6WA, 6AU6WB
						6137	-	6SK7
						6146	-	6293

*Parallel heater circuits only. Underline: Good or better substitute. (f) Foreign. (t) Temporary (emergency) substitute.

Tube	--	Substitute	Tube	--	Substitute	Tube	--	Substitute
6150	-	<u>5784WA</u>	6414	-	5965, 6829	6778	-	EC70F(f), 5718
6180	-	5692, 6SN7	6485	-	6AH6	6779	-	Z803U(f)
6186	-	6AG5	6487	-	EF70(f)	6829	-	5965, 6414
6187	-	<u>6AS6W, 6AS6,</u> <u>5725</u>	6488	-	EF73(f)	6893	-	2E26
6189	-	<u>12AU7WA, 12AU7</u>	6489	-	<u>EA76(f), EA71(f)</u> 5647	6906	-	BL643(f), E91H(f)
6201	-	<u>12AT7, 6060</u>	6550	-	6L6	6922	-	E88CC(f)
6202	-	6X4	6661	-	6BH6	7000	-	6J7
6221	-	5718	6662	-	6BJ6, E99F(f)	7199	-	<u>DB230A(f)</u>
6222	-	5719	6663	-	6AL5	7036	-	5915A
6223	-	5840	6669	-	6AQ5	7543	-	6AU6
6252	-	<u>QQVO3-28(t)</u>	6677	-	6CL6	7700	-	6C6, 1603
6265	-	6BH6	6678	-	6U8	8016	-	<u>1B3, 1G3,</u> <u>1J3, 1K3</u>
6267	-	EF86(f)	6679	-	12AT7	9003	-	5590, 9001
6277	-	3B28A(f)	6680	-	12AU7	A2521	-	6CR4
6345	-	1HT4	6681	-	12AX7	CK1013-	-	5517
6360	-	<u>QQVO3-10(f)</u>	6686	-	E81L(f), EL861(f)	X99	-	20 *
6373	-	EL79(f)	6687	-	E91H(f), 7036	X155	-	6BZ8, 6BC8, 6BQ7, 6BK7, 6BS8, 6BZ7
6374	-	EY84(f)	6688	-	E180F(f)	XXFM	-	7X7
6375	-	DC70(f)	6689	-	E83F(f)	XXL	-	<u>7A4</u>
6388	-	6388/443A						

*Parallel heater circuits only. Underline: Good or better substitute. (f) Foreign. (t) Temporary (emergency) substitute.

Every effort has been made to make this replacement guide complete and accurate. Nevertheless, there is always the possibility of a few errors of omission or commission. For this reason the publisher assumes no responsibility in connection with substitutions made in accordance with this guide.

If the tube for which a substitute is desired is not listed, this is probably because a change in socket or wiring would be necessary in order to use a different type tube or because no suitable substitute can be obtained.

Where a tube is to be substituted in a modern series string circuit, it is important to use only that type which has controlled warm-up time. Use of a tube lacking this feature may result in premature failure. For example a 6SN7GTA tube must not be substituted in a series string circuit for a 6SN7GTB, since the former lacks the controlled warm-up feature.

Certain tubes in the preceding lists may be substituted only in parallel connected circuits. These are indicated by an asterisk (*) after the tube designation. If no asterisk is shown, tube may be substituted either in series or parallel connected heater systems. In cases where the asterisk appears after a suggested substitute, it is necessary to know whether the heaters or filaments are connected in series or parallel. This information may be obtained readily without consulting a diagram or tracing the circuit. If a burnt out or defective tube is to be replaced, remove it from its socket. If all other tubes remain lit when the switch is turned on, the heaters are in parallel. If, upon removal of the defective tube, any other tubes show loss of heater glow, the removed tube is part of a series system hookup.

SECTION 2

SUBSTITUTES FOR FOREIGN TUBES

Tube	Substitute	Tube	Substitute	Tube	Substitute
1C1	- 1R5(t), DK91, X17	1R5SF	- 1AQ5	5B/250A	- 807, 5933, 807W, QV05-25
1C2	- 1AC6, 1AB6, DK92, X18, X20	2B21	- 2X2A, 2X2W, 879, 143D	5F22A	- 4-250A
1C3	- 1AB6, 1AC6*	2B94	- 5894, AX9903/5894	5F23A	- 4-400A
1C4	- 1A4P, 34	2H2B	- 3B28	5G24	- 5544
1C5	- DL35, N14, 1A5*	2CY5	- 2EA5, 2EV5	5H69A	- 869B
1D13	- 1A3	2H66	- 866A (See DCG4)	5J180 E	- 7876
1E3	- DC80	2K25	- 723A/B, K340	5M-HH3	- 5J6
1F1	- 1AJ4, 1AF4	2K26	- KS7-85	5P29	- 6CN6
1F2	- 1L4(t), DF92, 1U4, 1AF4*	2EV5	- 2EA5	5S1	- 807
1F3	- 1T4, DF91, W17	2T24	- 3C24, HK24G, 25TG,	5T20	- 250TL
1FD1	- 1AH5, 1AJ5, DAF96	2T25	- 8012A	5T21	- 250TH
1FD9	- 1S5, DAF91, ZD17, 1AF5*	2T26	- 826, GL826	5T30	- 450TL
1G45P	- 3C45, H45, ZG547, 5137	3F65	- 4-65A	5T31	- 450TH
1G50	- 2050, VT-245, GL2050, B2A, 1665	3G10	- 7E5, 1201, RGN1503	5T33	- 833A
1H16	- 816, HY886JR, NU866JR/816, GL816, VT-216	3G15	- C1A	5V5545	- 5545
1H35	- 1AB6	3G94	- 394A, WF394A	6/30L2	- 6GA8
1P1	- 3C4, 3E5, DL96, N25	4B13	- 813	6AM5	- EL91, N77, N144, 7D9
1P10	- 3S4, N17, 3Q4, DL92	4F15R	- 4X150A	6AM6	- 6064, EF91, 8D3, 6F12, SP6, Z77
1P11	- 3V4(t), N19, 3C4*, 3E5*, DL94	4G23	- 3C23	6AT7N	- 6DT8
		4G63	- 5563	6B32	- 6AL5, 5726, 6058, 6097, 6663
		4H32	- 4B32	6C9	- 6CU7*
		4H72	- 872A	6C10	- 6CU7*
		4H73	- 673	6CC42	- 5670, 5670WA
		4H88	- 8008	6D2	- 6AL5(t), 5726, 6097, 6058, 6663
		4R-HH2	- 4BS8	6DG7	- EF89
		4T16	- 100TL	6DL5	- EL95
		4T17	- 100TH	6E8	- 6A8(t)
		4Y25	- 807	6ECH80	- 6AN8

*Parallel heater circuits only

(t) Temporary substitute

Tube	Substitute	Tube	Substitute	Tube	Substitute
6ECL84	- 6DX8	7F57	- 8578	40PPA	- 7D3
6F10	- 6AC7, 6AB7, 6AC7W, 6AJ7, 6SD7*, 6SJ7*, 1852, 1853, 6006*, 6134, 5693	7T40	- 1000T	62CH	- 6CU7*
6F12	- 6AM6(t), 6064(t), EF91, SP6, 8D3, Z77	7T45	- 1500T	62DDT	- 6CV7, EBC41, DH150, DH718, 6LD3
6F16	- 6CJ5	8D3	- 6AM6, 6064, EF91, SP6, Z77, 6F12	62VP	- 6CJ5
6F18	- 6EC7	8D5	- 6BR7, 6059	63ME	- 6U5G
6F19	- 6BY7	8D7	- 6BS7	63T1	- 6AB8
6F21	- 6CQ6, 6065	8F66R	- 6166	63TP	- 6AB8
6F22	- 6CF8, 6267	8T21	- 9C21	64ME	- 6CD7(t)
6F50R	- 4X500A	8T21R	- 9C22	64SPT	- 6BX6
6FD12	- 6DC8, 7125	8T71R	- 5671	65ME	- 6BR5
6G5G	- 6U5G	9D6	- 6CQ6, 6065, EF92, VP6, W77	66KU	- 6BT4
6G45	- 5545+, 5685	9P9	- 9BM5	67PT	- 6CK5, BF61, EL41, N150
6C12	- 6AJ8	9T21	- 5770	108C1	- 0B2(t), 0B2WA(t), 6074, 6627, S860
6C16	- 6BL8	10C14	- 19D8	85A1	- 0E3(t)
6L12	- 6AQ8, ECC85, B719	10LD3	- 14L7	85A2	- 0G3
6L13	- 12AX7	10P18	- 45B5	121VP	- 12AC5, 10F9, HF121, UF41, W118, W145
6L16	- 6CW7	10PL12	- 50BM8	141TH	- 14K7, UCH42, X142
6L34	- 6AQ4, EC91, M8099	12E13	- 6CA7, 6L6*, 7027, 6L6GA*, 6L6GB*, 6L6G*, 7D11	150B2	- 6354, M8163, QS 1200
6LD3	- EBC41, DH718, 6CV7, DH150, 62DDT	13D1	- 25L6, 25A6, 6046, 25B6, 25C6, 25W6, 5824, KT32	150B3	- QS150/15
6LD12	- 6T8, 6AK8	13D2	- 6SN7GTB	150C2	- 0A2(t), 0A2WA(t), S856, 6626, 6073
6M1	- 6U5G(t)	13E1	- 7972	150C3	- 0D3, KD25, VR150
6M2	- 6CD7	14D12	- 8078	177DDP	- 17C8, 17N8, UBF80
6P9	- 6BM5	16P12	- 7974	311SU	- 31A3
6P15	- 6BQ5	17N8	- 17C8	403A/B	- 6AK5*, 5591, 5608, 5654*, 6096*, DP61
6P17	- 6AM5, 6516, EL91, M8082, N77, N144, QA2402, QM77	19D8	- 19AJ8	451PT	- 45A5, N142, UL41, UL46, 10P14
6Z31	- 6BX4, 6X4	19U3	- 19X3	7247	- 17DW8
7AN7	- 30L1, B319, PCC84	20D3	- 12AH8, PY80, U152, U309	8719	- 6AQ8
7D9	- 6AM5, 6516, 6P17, EL91, M8082, QN77, N77, N144, QA2042, QN77	30C1	- 8A8(t), 9A8(t), LZ319	18042	- 6086, TS53(t)
7D10	- 6CH6	30C15	- 9EN7	A11B	- 1W4
7D11	- 6CA7, 6L7*, EL34, 6L6GB*, 6L6GA*, 6L6GC*, KT66*, 5881*, 7027*	30F5	- 7ED7	A239	- 3B24W
7F25	- 4-1000A	30FL1	- 9GB8	A2521	- 6CR4
		30L1	- 7AN7(t)	A2674	- 436A+
		30P4	- 25GF6	ACS4	- 6076, AX9907R
		30P12	- 12FB5	AGR9950-	5869
		30P16	- 16A5	AGR9951-	5870
		30P18	- 15CW5		
		30PL1	- 13GC8		
		30PL12	- 16A8(t)		
		30PL13	- 16GK8		
		31A3	- 311SU, V311, U118		

* Parallel heater circuits only

(t) Temporary substitute

Tube	Substitute	Tube	Substitute	Tube	Substitute
AH205	- 8578	BPM04	- 6AQ5, 6AQ5A, 6BM5, 6005, 6BF5*, 6669, EL90	DCF60	- 1V6
AFX212	- 6D4			DCG4/1000G	- 866A, C866A, C866, RCA866A, UE966, UE966A, 966, 966A, WL866A/866, 3069
AH213	- 869B, 6508-, 3071	BR129	- 889R		GL866A/866, NU866A/866, UX866, RK866. T866A/866, CE866A/866, 3572, CV32, EE866A/866, Z225, GU12
AH217	- 872A, 872	BR191B	- 5762	DCG5	- 872A
AX224	- 3828	BK66	- 5550	DCG6/18	- 6693
AX230	- 4B32	BW129	- 889A	DCG6/6000	- 5869
AX4-250A	- 4-250A, 5D22, 4-250, X117, 4-250/5D22, 5D23/RK65	BW137C	- 9C21	DCG9/20	- 6508
AA91E	- 6AL5, 5726, 6058, 6097, 6663	C143	- 813	DCG12/30	- 5870
B36	- 12SN7, 12SX7	C144	- 829B	DCX4/1000	- 3B28
B65	- 6SN7, 6BL7*, 6SL7*, 5692.	C178A	- 5894	DD6	- 6AL5, 5726, 6058, -6097, 6663
B63	- 6A6, 6E6	C180	- 832A, VT286	DD7	- 6AM5(t), 6516(t)
B152	- 12A7, 12AT7WA, 12AU7, 12AV7*, 12AX7, 12AY7, 12AZ7*, 6060, 6201, 6679	C1108	- 6155	DDR7	- 6AM5(t), 6516(t)
B262	- 5B1, 215SG, S2, S21, K40B, PM12, S215, SG215A, S23, S24, SS210, 220SG	C1123	- 4D32	DET22	- 5861
B309	- 12AT7, 6201, 12AT7WA, 12AU7, 6060, 12AV7*, 6679, 12AX7, 12AZ7	C1134	- 6252	DF33	- 1N5GT, 1P5, Z14
B319	- 7AN7	C1135	- 5867	DF60	- 5678, XFR2
B329	- 12AU7(t), 12AU7WA(t), 5814, 5814A, 6067, 6189, 6680, 5963, 12AZ7*(t), 12BH7*(t)	CC82E	- 12AU7, 12AU7WA, 5814, 5814A, 6067, 6189, 6680, 5963, 12AU7A, 12AT7, 12AX7, 12AV7*	DF62	- 1AD4
B339	- 12AX7, 12AT7, 12AU7, 12AY7, 12AZ7*, 12AD7, 5751*, 6057, 6681, ECC83			DF66	- 5676
B1109	- 3C24	CR139	- 827R	DF67	- 6008
B1135	- 5867	CR192	- 6166	DF91	- 1T4(t), 1L4(t), 1AF4*(t), 1U4(t)
B142	- 833A	CR1100	- 6075	DF92	- 1L4(t), 1U4(t), 1AF4*(t)
BF61	- 6CK5	CR1101	- 6181	DF96	- 1AF4, 1AJ4
BK24	- 5552A	CV16	- REL46	DF97	- 1AN5
BK24A	- 6347+	CX1119	- 7384	DF652	- 1AD4
BK34	- 5553	D2M9	- 6AL5, 5726, 6058, 6097, 6663, E91AA	DF703	- CK5886
BK42	- 5551A	D21	- 3D21	DF904	- 1U4, 1T4, 5910
		D27	- 6AL5, 6AK5	DH63(M)	- 6Q7/GT(t)
		D63	- 6H6G, 1638, OM3	DH77	- 6AT6(t), 6066(t), 6AV6(t), 6BF6(t), 6BK6(t), 6BT6(t)
		D77	- 6AL5, 5726, 6058, 6097, 6663	DH81	- 7B6
		D152	- 6AL5, 5726, 6058, 6097, 6663	DH149	- 7C6
		DA90	- 1A3, 1D13	DH150	- 6CV7, 6LD3, 62DDT, EBC41, DH718
		DAC32	- 1H5(t), HD14	DH718	- 6CV7, 6LD3, DH150, 62DDT, EBC41,
		DAF91	- 1S5(t), 1AF5*		
		DAF92	- 1U5, 1DN5		
		DAF96	- 1AH5, 1AJ5, 1FD1		
		DC70	- 6375		
		DC80	- 1E3		
		DCC90	- 3A5		

*Parallel heater circuits only

(t) Temporary substitute

Tube	Substitute	Tube	Substitute	Tube	Substitute
DH719	- 6T8A, 6AK8	E90F	- 6265, 6661, 6BH6	EC81	- 6R4
DK32	- 1A7G(t), 1B7(t)*, 1C7*(t)	E91AA	- 6AL5, 5726, 6058, 6097, 6663	EC84	- 6AJ7
DK91	- 1R5(t), X17, 1C1	E91H	- 6687, 7036	EC86	- 6CM4
DK92	- 1AC6, 1AB6, X18, X20	E91N	- 5727, 5757, 20A3	EC90	- 6C4
DK96	- 1AB6, 1AC6*, 1AF4, X25	E95F	- 5654	EC91	- 6AQ4, 6L34, M8099
DL29	- 3D6, 3LF4*, 1299	E99F	- 6662, 6BJ6, 7694	EC92	- 6AB4
DL33	- 3Q5, 3B5, 3C5, N17	E130L	- 7534	EC93	- 6BS4
DL35	- 1C5(t), 1A5*(t), N14	E180CC	- 7062	EC94	- 6AF4, 6AF4A
DL36	- 1Q5, 1T5*, 1A5*	E180F	- 6688	EC95	- 6ER5
DL63	- 1639	E182CC	- 7119	EC97	- 6FY5
DL67	- 6007, 5913	E188CC	- 7308	ECC33	- 6SN7*(t)
DL70	- 1M3, 1N3	E280F	- 7722	ECC35	- 6SL7*(t)
DL82	- 7B6	E283CC	- 5751(t)	ECC40	- 6N7*(t)
DL91	- 1S4(t)	E810F	- 7788	ECC55	- 5861
DL92	- 3S4(t)	E2754	- 417A	ECC81	- 12AT7
DL93	- 3A4(t)	EA52	- 6923	ECC82	- 12AU7(t)
DL94	- 3V4, 3C4*, 3E5*	EA76	- 6489, 5647	ECC83	- 12AX7
DL95	- 3Q4, 3S4, N18	EAA91	- 6AL5(t), 5726, 6058, 6097, 6663	ECC84	- 6CW7(t)
DL96	- 3C4, 3V4, 3E5	EAA901	- 6AL5(t), 5726, 6058, 6097, 6663	ECC85	- 6AQ8
DL98	- 3B4(t)	EAA901S-	6AL5	ECC86	- 6GM8
DL620	- 5672	EAA9015-	5726	ECC88	- 6DJ8
DL651	- CK546	EABC80	- 6AK8, 6T8, 6R8	ECC89	- 6FC7
DL 652	- 5672	EAF42	- 6CT7	ECC91	- 6J6(t)
DM70	- 1M3	EB34	- 6H6*(t), 1638*(t)	ECC180	- 6BQ7A
DM71	- 1N3	EB91	- 6AL5(t), 5726(t), 6058(t), 6097(t), 6663(t)	ECC186	- 5814, 6067, 7316
DM160	- 6977	EBC33	- 1639(t)	ECC189	- 6ES8
DP61	- 6AK5	EBC42	- 6CU7	ECC803S-	12AX7, 6681
DQ4	- 8698	EBC41	- 6LD34, 6CV7, DH150, DH718, 62DDT	ECC801S-	6201
DQ6	- 6508	EBC80	- 6BD7	ECC802S-	12AU7
DY30	- 1B3, 1G3, 1J3, 1K3	EBC90	- 6AT6(t)	ECC960	- 5920
DY80	- 1X2A, 1X2B, 1AX2	EBC91	- 6AV6(t)	ECF80	- 6BL8, 6C16
DY86	- 1S2, 1S2A, 1H2	EBF80	- 6N8	ECF82	- 6U8
DY87	- 1H2	EBF81	- 6AD8	ECF86	- 6HG8
E1C	- 955	EBF83	- 6DR8	ECH35	- 6E8
E1F	- 954	EBF86	- 6267	ECH42	- 6J7, 6C9, 6CU7*
E80F	- 6084(t)	EBF89	- 6DC8, 7125	ECH81	- 6AJ8
E81L	- 6686	EC55	- 5861	ECH83	- 6DS8
E80CC	- 6085	EC70	- 5718, 6778	ECH113	- 6CU7*
E80CF	- 7643	EC80	- 6Q4	ECL80	- 6AB8
E80L	- 6227			ECL82	- 6BM8
E80T	- 6218			ED2	- 6AL5, 5726, 6058, 6097, 6663
E83F	- 6689			EF22	- 7G7
E88CC	- 6922			EF70	- 6487(t)
E90CC	- 5920			EF71	- 5899
				EF72	- 5840
				EF73	- 6488
				EF76	- 6489
				EF80	- 6BX6
				EF81	- 6BH5

*Parallel heater circuits only (t) Temporary substitute

Tube	Substitute	Tube	Substitute	Tube	Substitute
EF82	- 6CH6	EY51	- 6X2	HL92	- 50C5
EF85	- 6BY7	EY70	- 5641	HL94	- 30A5
EF86	- 6CF8, 6267, Z729	EY80	- 6U3	HM04	- 6BE6
EF89	- 6DA6	EY81	- 6R3	HY61	- 807
EF89F	- 6DG7	EY82	- 6N3	HY90	- 35W4
EF91	- 6AM6	EY84	- 6374, 6443, R18	KD21	- 0A3
EF92	- 6CQ6, 6065	EY86	- 6S2	KD24	- 0C3
EF93	- 6BA6(t), 5749	EY87	- 6S2A	KD25	- 0D3
EF94	- 6AU6(t)	EY88	- 6AL3	KF35	- 1E5
EF95	- 6AK5(t)	EZ35	- 6X5/GT(t)	KK32	- 1C7, 1D7*
EF96	- 6AG5	EZ40	- 6BT4	KL35	- 1F5, 1J5
EF97	- 6ES6	EZ80	- 6V4	KT32	- 25L6GT
EF98	- 6ET6	EZ81	- 6BW4*(t), 6CA4*(t)	KT63	- 6J7
EF183	- 6EH7	EZ90	- 6X4, 6BX4, 6AV4*	KTW63	- 6K7
EF184	- 6EJ7	EZ91	- 6AV4, 6BX4, 6X4	KT66	- 6L6*(t)
EF730	- 5636	GZ31	- 5T4	KT81	- 7C5
EH90	- 6CS6	GZ34	- 5AR4	KT88	- 6CA7
EH900	- 5915	F7001	- 7001	L63	- 6J5(t), 6C5(t)
EK90	- 6BE6	F7004	- 5842	L77	- 6C4
EL33	- 6M6G	FX219	- 5C22, HT415	LN152	- 6AB8(t)
EL34	- 6CA7	FX227	- 6130, 3C45+	LZ319	- 8A8(t), 9A8(t)
EL35	- 6L6*	FX231	- KU25	LZ329	- 9A8
EL36	- 6CM5	G5B	- 872A	M8079	- 6AL5, 5726, 6058, 6097, 6663
EL37	- 6L6, 5881	G40	- 869B	M8081	- 6J6, 6J6WA, 6099, 6030, 5101, 6106
EL38	- 6CN6	G100A	- 857B	M8082	- 6AM5, 7D9, 6P17, EL91, N77, N144, QA2402, QN77
EL41	- 6CK5	GU-20/21	- 4B32+	M8099	- 6AQ4, 6L34, EC91
EL70	- 7001	GZ30	- 5Z4	M8100	- 6AK5
EL80	- 6M5	GZ32	- 5V4	M8135	- 6CH6
EL81	- 6CJ6	GZ34	- 5U4G(t), 5U4GA(t), 5U4GB(t), 5Z4(t)	M8136	- 12AU7
EL83	- 6CK6(t)	H52	- 5U4GA, 5AU4, 5AX4, 5U4GB, 5Z4, 5Y4	M8163	- 6354
EL84	- 6BQ5	H63	- 6F5	M8190	- 5783
EL85	- 6BN5	H5015	- 3D21	M8204	- 5727
EL86	- 6CW5	HAA91	- 12AL5	M8206	- 0B3
EL90	- 6AQ5	HABC80	- 19T8(t)	M8212	- 6AL5, 5726 6058, 6097, 6663
EL91	- 6AM5, 6516, 7D9, 6P17, M8082, N77, N144, QA2402, QN77	HBC90	- 12AT6(t)	ME1401	- 5802
EL95	- 6DL5	HBC91	- 12AV6(t)	MT17	- 5557+
EL803	- 6CK6	HCC85	- 17EW8	MT5545	- 5545
EL821	- 6CH6(t)	HCH42	- 14K7	MW36-24	- 14EP4*
EL822	- 6CH6	HCH81	- 12AJ7	MW43-61	- 17QP4*
EL861	- 6686	HD14	- 1H5(t), DAC32	N14	- 1C5(t), 1A5(t), DL35
ELL80	- 6HU8	HD30	- 3B4	N15	- 3Q5, N16
EM34	- 6CD7	HF93	- 12BA6(t)	N16	- 3Q5, N15
EM35	- 6U5G	HF94	- 12AU6(t)	N17	- 3S4(t)
EM80	- 6BR5	HK90	- 12BE6	N18	- 3Q4, 3S4, DL95
EM84	- 6FG6	HL90	- 19AQ5		
EN70	- 5641				
EPF83	- 6DR8				
EQ80	- 6BE7				
ESW892	- 892				

*Parallel heater circuits only (t) Temporary substitute

Tube	Substitute	Tube	Substitute	Tube	Substitute
N19	- 3V4(t), 1P11	PL345	- 3C45	QE05/40H	- 6159
N25	- 3E5	PL435	- 4C35	QE08/200	- 7378
N63	- 6AG6	PL5551A	- 5551A	QE06/50	- 807
N77	- 6AM5, 7D9, 6P17, EL91, M8082, N144, QA2402, QN77	PL5552A	- 5552A	QQC04/15	- 5895
		PL5553A	- 5553A	QQE03/12	- 6360
		PL522	- 5C22	QQE03/20	- 6252, AX9910
N144	- 6AM5(t)	PL5544	- 5544	QQE04/5	- 7377
N379	- 15CW5(t)	PL5545	- 5545	QQE04/20	- 832 A VT-286
N709	- 6BQ5(t)	PL2D21	- 2D21	QQE06/40	- 829B, 5894
N727	- 6AQ5	PL4-400A	- 4-400A	QQV03-10	- 6360
NR68	- 6Q7G	PL4C35	- 4C35	QQV03/12	- 5763, A4541H
N78	- 6BJ5	PL4D21	- 4D21	QQV03-20A	- 6252
N142	- 45A5	PL5C22	- 5C22	QQV03-28	- 6252(t)
N147	- 6AG6	PL17	- 5557	QQV04/15	- 832A, VT286
N148	- 7C5(t)	PL57	- 5559	QQV06-40A	- 5894, AX9903
N150	- 6CK5	PL1267	- 0A4G, 1267	QQV07-40	- 829B, NU829B, GL829, RK829, RK829B, RC828
N152	- 21A6(t)	PL5555	- 5555	QS150/30	- 0A2, 6626
N153	- 15A6	PL5557	- 5557	QS1205	- 0A3
N309	- 15A6	PL5559	- 5559	QS1206	- 0C3
N359	- 21A6	PL5684	- 5684	QS1207	- 0A2, 6073, 6626
NR81	- 6K7G	PL5822	- 5822	QS1208	- 0B2, 6074, 6627
N329	- 16A5(t)	PL6011	- 6011	QS1209	- 5651
0M3	- 6H6, 1638	PL6574	- 6574	Q T1251	- 5823(t)
OSW3109	- 6H6, 1638, 0M3	PL6755	- 6755+	QV1-150A	- 4X150A, X424D
		PM04	- 6BA6(t)	QV20- P18	- 4PR60A
P2-40B	- 829B, NU829, RK829, RK829B, RCA828, GL829	PM05	- 6AK5(t)	QV05-25	- 807
		PM07	- 6AM6(t)	QY2-100	- 813, GL813, WL813, NU813, T813, VT144
P807	- 807	PY80	- 19X3(t)	QY-3-125	- 4D21, 4-125A 6155, X103, 4D21/4-125A
PABC80	- 9AK8	PY81	- 17Z3	QY4/65	- 4-65A
PCC84	- 7AN7	PY82	- 19X3(t), 19Y3(t)	QY4/250	- 4-250A, 5D22, 6156
PCC85	- 9AQ8	QA2404	- 6AL5, 5726, 6058, 6097, 6663	QY5-500	- 6079
PCC86	- 4CM4	QB2/250	- 813, WL813, GL813, NU813, T813, VT144	QY5-3000A	- 6076
PCC189	- 7ES8(t)	QB3/200	- 4-65A	QY5-3000W	- 6075
PCC88	- 7DJ8	QB3/300	- 6155		
PCC89	- 7FC7	QB3.5/750	- 5D22 4-250, X117, 4-250/5D22		
PCF80	- 8A8(t), 9A8(t)	QB4/110C	- 7527		
PCF82	- 9U8, 9U8A	QB5/1750	- 6079		
PCL82	- 16A8	QBL4/800	- 4X500A		
PCF86	- 7HG8	QBL5/3500	- 6076		
PCL84	- 15DQ8	QBW5/3500	- 6075		
PE1/100	- 6083, AX9909	QD77	- 6AL5, 5726, 6058, 6097, 6663		
PE04/10E	- 837, RK837, WL837, GL837, A4002B, VT101	QEL1/150	- 4X150A, X424D		
PL21	- 5727	QE05/40	- 6146		
PL36	- 25E5(t)	QE05/40F	- 6883		
PL81	- 21A6				
PL82	- 16A5				
PL83	- 15A6, N153				
PL84	- 15CW5				

*Parallel heater circuits only (t) Temporary substitute

Tube	Substitute	Tube	Substitute	Tube	Substitute
R16	- 1T2	TB4/800	- 250TH	U52	- 5U4G, 5AS4,
R52	- 5Z4, 5V4G,	TB5/2500	- 7092		5Z4, 5AW4,
	5V4GA	TBL2/300	- 7004		5U4GA, 5U4GC,
REL46	- CV16	TBL6/14	- 7804		5931, 5AX4
RG3-250A-866A		TBL6/4000	- 7753	U70	- 6X5GT(t)
RG4-3000	- 6693	TBL6/6000	- 5923	U76	- 39/44
RGN1503	- 7E5	TBL7/8000	- 6961	U78	- 6X4(t)
RR3-250	- 3B28	FBL12/38	- 7806	U145	- 31A3
RR3/1250	- 4B32	TBL12/100	- 6078	U147	- 6X5GT(t)
RS613	- 5866	TBW6/14	- 7805	U149	- 7Y4(t)
RS630	- 5867, 6569+	TBW6/6000	- 5923	U150	- 6BT4
RS631	- 5868	TBW7/8000	- 6960	U151	- 6X2
RS635	- 7092+	TBW12/38	- 6077	U153	- 17Z3
RS685	- 4D21, 4-125A,	TC552-B	- 834	U154	- 19Y3(t)
	6155+	TD1-100A	- 2C39A,	U191	- 19CS4
RS686	- 5D22, 4-250A,		2C39WA,	U192	- 19Y3
	6156+		X474	U319	- 19Y3(t)
RS687	- 6079	TD03-10	- 5861(t)	U381	- 38A3
RS1002	- 4-250A+, 6156+	TH3B24W	- 3B24W	U718	- 6BT4
RS1006	- 5866	TH5C22	- 5C22	UABCR80	- 28AK6
RS1007	- 6155	TH100TH	- 100TH	UAF42	- 12S7
RS1016	- 5868	TH250TH	- 250TH	UBC41	- 14L7
RY12-100	- 8020	TH833A	- 833A	UBF80	- 17N8, 17C8
S2P20	- 7973	TH1257	- 1257	UC92	- 9AB4
S1E12	- 7971	TH5949	- 5949	UCC85	- 26AQ8
SD128E	- 5634	TH6885	- 6885	UCH42	- 14K7
SD719	- 1AB5	TH6886	- 6886	UCH81	- 19D8, 19AJ8
SN152	- 6AB8	TH6587	- 6587	UCL82	- 50BM8
SN944	- 5633	TH6942	- 6942	UF41	- 12AC5
SN946	- 5647	TH5949	- 5949	UF89	- 12DA6
SN979	- 5718	THF6017	- 6017	UL41	- 45A5
SP6	- 6AM6(t)	THF6018	- 6018	UL84	- 45B5
STV/10	- 0G3	THF6019	- 6019	UQ80	- 12BE7
STV108/30	- 0B2,	TS54	- 6689	UU12	- 6CA4
	0B2WA, 6627	TY2-125	- 5866	UY41	- 31A3
STV150/30	- 0A2,	TY3-250	- 5867	UY85	- 38A3
	0B2, 6073	TY4-350	- 833A	UY87	- 807
SV2C39A-2C39A,		TY4-500	- 5868	V2M70	- 6X4
	2C39WA, X474,	TY6-800	- 7092 +	V40	- 8020
	3X100A11/2C39	TY6-5000A	- 5924	V61	- 6BT4
SV4-150A	- 4-150A	TY6-5000W	- 5923	VP6	- 6CQ6
SV4X150A	- 4X150A	TY7-6000A	- 6961	VR54	- 6H6, 1638
SV813	- 813	TY7-6000W	- 6960	VR105/30	- 0C3
SV828	- 828	TY12-25A	- 6618	VR150/30	- 0D3
SV5545	- 5545	TY12-25W	- 6617	W17	- 1T4(t)
T2MO5	- 6J6, 6J6WA,	TY12-50A	- 6077	W25	- 1AF4, 1L4*,
	6101	TY12-50W	- 6078		1U4*, DF96
T66G-GT-884		TY16G	- 885+	W61	- 6K7
T450S	- 7915	U25	- 2L2	W63	- 6K7G(t)
TB2.5/300	- 5866	U37	- 1T2	W76	- 12K7
TB3/350	100TH, VT218,	U41	- 1B3	W77	- 6065(t)
	EE100TH,	U43	- 6X2	WD142	- 12S7
	3-100A4/100TH	U50	- 5Y3G, 5U4G,	W149	- 7B7
TB3/750	- 5867		5U4GA, 5U4GB,	W179	- 6BY7(t)
TB4/1250	- 5868		6087, 6106	W719	- 6BY7

*Parallel heater circuits only (t) Temporary substitute

Tube	Substitute	Tube	Substitute	Tube	Substitute
W727	- 6BA7	XAA91	- 3AL5	XXB	- 3C6
WD709	- 6N8	XC95	- 2ER5	Y61	- 6U5
X14	- 1A7(t), 1B7(t), 1C7(t)	XCC82	- 7AU7	Y63	- 6U5
X17	- 1R5(t), DK91	XCC189	- 4ES8	Z14	- 1N5GT, 1P5, DF33
X18	- 1AC6, 1AB6, X20	XF94	- 3AU6, 3BA6	Z63	- 6J7G(t)
X20	- 1AC6, 1AB6,	XF183	- 3EH7	Z77	- 6AM6(t)
X25	- 1AB6	XF184	- 3EJ7	Z152	- 6BX6(t)
X63	- 6A8(t)	XFR1	- 1AD4	Z300T	- 0A4(t), 1267(t)
X64	- 1612	XG5-10	- 6786	Z719	- 6BX6
X71M	- 12K8	XG5-500	- 5557	Z729	- 6267
X76M	- 12K8	XH3-045	- 3C45, H45, CG547, 5137	Z803U	- 6779
X79	- 6AE8	XH16-200	- 5C22	Z900T	- 5823
X81M	- 7S7(t)	XH25-500	- 5949	ZD17	- 1S5
X148	- 7S7(t)	XHB-100	- 4C35	ZD152	- 6N8
X150	- 6CU7*	XL84	8BQ5		
X719	- 6BX6	XR1-1600A	- 5796, 8063		
X727	- 6BE6	XR1-3200	- 5544, 7981		
		XR1-6400A	- 6807, GL6807		

*Parallel heater circuits only (t) Temporary substitute

Note: Some manufacturers of foreign tubes have suggested U. S. A. substitutes, without supplying adequate specifications. Hence, there is a possibility in a few instances, that substitutes may not equal the performance of tubes being replaced.

SECTION 3

"NO SUBSTITUTE" TUBES

Many Replaceable by Substitutes Through Easy Conversion

The following list contains tubes both old and new, which, at the time this book went to press, had no DIRECT substitutes able to give satisfactory performance.

We are pleased to announce a unique Consultation Service which will supply the designation of a satisfactory substitute together with the information needed to make minor electrical and/or other changes in order to enable the replacement to function in the place of the original tube.

To obtain this information send \$1.00 for each tube to be substituted, plus stamped self-addressed envelope to Harry G. Cisin, Consulting Engineer, Amagansett, N. Y. 11930. If no substitute can be adapted your dollar will be refunded. This information is available only with respect to the tubes in the following list.

SPECIAL FREE OFFER

With each order you will receive ABSOLUTELY FREE a copy of H. G. Cisin's SUPPLEMENTARY tube replacement guide containing 1274 direct USA tube substitutions not in this book. The SUPPLEMENTARY book also contains additional substitutes for foreign tubes and also for picture tubes. Sold separately, SUPPLEMENTARY book costs 50¢.

1AD5	4BN6	5J6	6BK5	6EQ7	6GY8	8B8	11
1AG4	4CX6	5T8	6BN6	6ET7	6H4GT	8B10	11AR7
1F6	4CX7	5V6GT	6BT8	6EU7	6HB5	8CM7	11C5
1LD5	4CY5	5X8	6BU5	6EU8	6HB6	8CN7	11CY7
1LH4	4GK5	6A3	6BV8	6EV7	6HW8	8CS7	11JE8
1V2	4GW5	6AG11	6BW8	6EW7	6J8G	8CW5	12AB5
1Z2	5AM8	6AH4GT	6BY8	6EZ7	6J11	8CY7	12AF3
2AH2	5AN8	6AH5G	6C9	6FG7	6JC8	8EM5	12AL8
2CW4	5AQ5	6AL11	6C10	6FJ7	6JH9	8ET7	12AL11
2E24	5AS8	6AN6	6CH8	6FM7	6JK8	8JK8	12AQ5
2EN5	5AT4	6AQ7GT	6CK4	6FM8	6JK11	8SN7GTB	12AX3
2FV6	5AT8	6AR5	6CL5	6FQ7	6M3	9AU7	12AY3
2FY5	5AZ3	6AR7GT	6CM6	6FV6	6M11	9BR7	12B3
2GW5	5AZ4	6AR8	6CM7	6FW5	6N4	9CL8	12B8GT
2H21	5BC3	6AR11	6CN7	6G11	6P7G	9DZ8	12BA7
2J2	5BT8	6AS8	6CQ8	6GB5	6Q11	9EF6	12BK5
2V3G	5BW8	6AV6	6CR5	6GC5	6R6G	9X8	12BW4
3A2	5CH8	6AV11	6CR6	6GE5	6S6GT	9BR7	12BZ6
3BC5	5CU4	6AW7GT	6CR8	6GE8	6S8GT	9BW6	12CR5
3BN6	5DJ4	6AX3	6CS5	6GF5	6T6	9DZ8	12CR6
3DG4	5DH8	6AZ8	6CU8	6GJ5	6V8	9EF6	12CS5
3ES5	5EH8	6B10	6D10	6GK6	6X6G	9GB8	12CT8
3GW5	5ES8	6BA4	6DN6	6GM5	6Y3G	9X8	12DB5
3SF5	5EU8	6BA7	6DR4	6GT5	7K7	10C8	12DE8
4AV6	5FG7	6BC4	6DZ8	6GW5	7Q7	10DA7	12DF5
4BN4	5GX6	6BF8	6EH8	6GW8	7W7	10EW7	12DJ8

12DK5	17GK5	50FA5	6350	7137	7604	8077
12DK6	17GT5	50FY8	6352	7156	7619	8078
12DK7	17H3	50X6	6398	7167	7630	8079
12DL4	17HC8	55N3	6417	7190	7631	8081
12DM4	17JK8	60DV3	6419	7191	7687	8082
12DT5	17R5	60E3	6463	7192	7695	8083
12DU7	18	60EH5	6483	7205	7698	8094
12DV7	18A5	60FX5	6519	7208B	7700	8136
12DV8	18DZ8	65C7, Z7	6520	7212	7718	8143
12DW8	18HB8	70A7GT	6525	7229	7720	C2044
12DY8	19	70L7GT	6526	7230	7757	CH1046
12DZ8	19DE7	83V	6550	7231	7763	CK510AX
12EC8	19HV8	90	6611	7232	7768	CK526AX
12EL6	19J6	117Z3	6612	7236	7788	CK527AX
12EM6	19V8	117Z4GT	6763	7246	7789	CK533AX
12ET8	19X8	407A	6792	7258	7792	CK534AX
12F8	20EQ7	1237	6830	7266	7794	CK542DX
12FA6	20EZ7	5594	6831	7296	7795	CK546DX
12FQ8	20J8	5618	6832	7316	7796	CK547DX
12FR8	21EX6	5690	6840	7318	7800	CK549DX
12FV7	22BH3	5696	6872	7327	7804	CK1024
12FX8	22DE4	5838	6873	7358	7815	CK1054
12FY8	25B8GT	5839	6877	7370	7837	GB-6814
12G8	25BK5	5841	6887	7400	7838	GB-6922
12CG6	25CN6	5845	6900	7401	7839	GB-7327
12GE5	25CR5	5857	6901	7408	7841	
12GJ5	25D8GT	5879	6913	7439	7843	
12GT5	25DK4	5947	6919	7440	7851	
12H4	25DT5	5950	6943	7441	7855	
12J8	25E5	5993	6944	7444	7861	
12K5	25F3	6004	6945	7452	7868	
12S8GT	25X4	6012	6946	7462	7869	
12U7	25X6GT	6092	6947	7489	7892	
12X4	25Z3	6094	6948	7490	7899	
13EM7	26D6	6101	6955	7492	7900	
14A4	27GB5	6119	6973	7494	7950	
14B8	28GB5	6135	6977	7495	7962	
14F8	28Z5	6140	6983	7496	7963	
14G6	32ET5	6142	7027	7498	7976	
14Q7	32L7GT	6143	7044	7499	7979	
15	35B5	6145	7054	7500	7983	
15A8	35C3	6184	7055	7502	7995	
15AF11	35CD6GA	6203	7056	7521	8034	
15EW6	35D5	6213	7057	7527	8042	
15G	35DZ8	6215	7058	7541	8043	
16GK6	35HB8	6216	7059	7547	8044	
16GK8	35Y4	6224	7060	7548	8056	
17AV5GA	50A1	6245	7061	7578	8058	
17C9	50A5	6264	7077	7586	8063	
17DE4	50BK5	6281	7079	7587	8064	
17DM4	50CD4	6308	7083	7589	8068	
17GJ5	50CD6G	6332	7105	7591	8070	

When ordering Consultation Service, be sure to give as much information as possible regarding the set for which replacement tube is desired. For example, if set is an AC-DC radio, give type designations of the other tubes in the set. If tube in question is part of a series string heater circuit give all type designations. Wherever possible give model and chassis numbers.

A CISIN'S BEST SELLER SERVICE BOOK



**INCLUDING
FOREIGN
SUBSTITUTIONS**

**CONDENSED
EDITION**

**PRICE
50
CENTS**

NEW

TV

**VOLUME
TWELVE**

AND RADIO

TUBE

SUBSTITUTION

Published by
HARRY G. CISIN
Amagansett, N. Y.

GUIDE

HARRY G. CISIN, Publisher
Amagansett, N. Y.